# Liebert® PowerSure® Panel TVSS Surge Suppression Solutions For Distribution Panels



Electric power line disturbances such as high voltage transients can disrupt or damage sensitive electronic equipment — causing a major loss in productivity and money. Liebert understands this problem and offers the Liebert PowerSure® Panel Low and Medium Exposure surge suppression systems — the reliable way to keep these power problems from getting into your facility in the first place.

- Liebert PowerSure® Panel
  Low Exposure Designed for use
  on branch panels or equipment in
  low exposure locations. Available
  up to 100kA/ph ase surge current
  capacity. LED status indication and
  Form C contacts for remote
  indication are standard.
- Liebert PowerSure® Panel

  Medium Exposure Offers

  protection from transients on

  distribution panels or any medium

  exposure location.

Available in 100kA/phase and 160kA/phase, all mode and two mode protection, small footprints, NEMA 12 enclosure, silver link fusing with the rmal protection, all voltage and phase configurations, 5-year warranty.

## Liebert PowerSure® Panel TVSS Technical Specifications

	Low Exposure	Medium Exposure	
Connection Type	Parallel	Parallel	
Operating Voltage Range	±15%	±15%	
Surge Current Capacity	25kA, 50kA or 100kA	100kA or 160kA	
Fault Current Rating (AIC)	22kAIC	65kAIC	
Dimensions	4.72"x4.72"x2.36"	(160 kA units) 8"x6"x4"	
		(100 kA units) 6"x4"x3"	
Operating Frequency Range	47-63 Hz	47–63 Hz	
Capacity	Continuous	Continuous	
EMI/RFI Attenuation	40 dB typical	40 dB typical	
Response Time	<0.5 nanoseconds	<0.5 nanoseconds	
Dry Contract rating	125 VAC, 8.0A, 1.0pf	125 VAC, 8.0A, 1.0pf	
Operating Temperature	-40°C to +50°C	-40°C to +50°C	
Operating Humidity	0% to 95%	0% to 95%	
Status Indication	LED, Dry Contacts	LEDs, Dry Contacts	
Certifications	UL 1449, CUL(CE-optional)	UL 1449, CUL	
Warranty	5-Years	5-Years	

## UL 1449 (second edition) Classification

	Low Exposure	Medium Exposure
120 Volt systems	400 Volts all modes	400 Volts all modes
208 thr ough 277 V olt systems	800 Volts all modes	800 Volts all modes
480 Volt systems	1,500 Volts all modes	1,500 Volts all modes

## Ordering Information

### **Building a Low and Medium Exposure Model Number:**

Examples

1

<u>LPL 123</u> (Low Exposure Unit) <u>LPM 123</u> (Medium Exposure Unit) (use Model ID column when determining 1, 2, 3 portion of Model Number)

No	Nominal Voltage Requirements			Model ID
	L-N	L-L	L-G	
-	120	N/A	120	<u>120</u>
-	120	208	120	<u>120</u>
-	120	240	240	<u>120</u>
-	N/A	208	208	208
-	230	400	230	230
	N/A	240	240	240
-	277	480	277	277
-	N/A	400	400	400
	N/A	480	480	480

System Configuration		Model ID
-	Single (2 Wire + Gnd)	N or L
-	Split (3 Wire + Gnd)	<u>s</u>
-	Wye (4 Wire + Gnd)	Y
	Delta Hi-Leg (4 Wire + Gnd)	Н
	Delta (3 Wire + Gnd)	<u>D</u>

Surg	e Current Capacity	Model ID	
(Low	Low Exposure)		
•	100 kA/Phase (L-N: 50 kA + L-G: 50 kA; N-G: 50	<b>100</b> kA)	
-	50 kA/Phase (L-N: 25 kA + L-G: 25 kA; N-G: 25	<b>50</b> kA)	
	25 kA/Phase (L-N: 25 kA; N-G: 25 kA)	25-2	
(Med	ium Exposure)		
-	160 kA/Phase (L-N: 80 kA + L-G: 80 kA; N-G: 80	<b>160</b> kA)	
-	100 kA/Phase (L-N: 100 kA; N-G: 100 kA)	100-2	

### **Country Office**

Emerson Network Power (India) Private Ltd. Plot No. C-20, Road No. 19, Wagle Estate, Thane (W), Maharashtra - 400 604. India.

Tel.: 91-22-33154400 Fax: 91-22-25828358

Toll Free No 18002096070

Email: marketing.india@emerson.com

## FROST & SULLIVAN

Voice of Customers UPS Awards 2004-05 for Product Line & Customer Service Awards in IT, Telecom, Large Enterprise & Hospitals and Customer Service Leadership Award in BFSI





Emerson Among Top 50 On Fortune Survey Of "Worlds Most Admired" Companies.

Best IT Hardware Company Maharashtra IT Award 2006-07





www.emersonnetworkpower.com

#### **Emerson Network Power.**

The global leader in enabling Business-Critical Continuity

AC Power

Connectivity

DC Power

Embedded Computing

Embedded Power

Monitoring

Outside Plant

Power Switching & Controls

Precision Cooling

Racks & Integrated Cabinets

Services

Surge Protection

While every precaution has been taken to ensure accuracy and completeness in this brochure, Emerson Network Power assumes no responsibility, and disclaims all liability for damages resulting from use of this information or for any errors or omissions.

For disposal of Batteries Please visit the below link: http://www.cpcb.nic.in/divisionsofheadoffice/hwmd/lead.pdf

Note: Specifications & Features may vary based on the condition.

Emerson Network Power and the Emerson Network Power logo are trademarks and service marks of Emerson Electric Co. © 2010 Emerson Electric Co.